



PM-01 / PM-06

Paging Microphones

Features

- Work with PS-2406/4800
- Slave or Master mode
- Paging up to 6 zones (PM-06)

PM-01 is a desktop microphone designed to operate with PS-2406 / PS-4806. It can be used as a slave unit or as a master unit through a back panel selector. Up to 3 PM-01 can be connected to the PS devices which supply the power without the need of extra connection.

PM-06 is a paging station controlling up to six zones separately with an "ALL ZONE" function. PM-06 can also be used as a slave or as a master unit through a dip switch selector. In addition to the Mic input a RCA input is available for an external sound source. Audio signal is converted in AES3 through Cat5e cable which allows a distance connection over 100 meters. PM-06 has a built-in chime function where the sound can be modified by connecting the USB port to a PC. It can launch up to 6 messages stored in the PS main frame and controls over Play/Stop/Repeat functions.



Specifications

PM-01

Front Controls	Push to Talk switch with red LED
Rear Controls	DIP Switches for Priority and Chimes ON/OFF MASTER / SLAVE selector
Output	OUTPUT: RJ-45 for connection to PS-2406/4806 LINK: RJ-45 for daisy-chain connection with two additional PM-01

PM-06

Front Controls	ZONE 1-6 Push to Talk switches, ALL ZONE push to talk switch MESSAGE BANK switch x 6 Message START/STOP, REPEAT/STOP switches LED indicators: POWER green, SEND yellow, BUSY red USB for audio messages edition
Rear Controls	CH1 / PROG selector DIP Switches for Slave and Priority ON/OFF Audio Out volume
Input	AUX IN (-10dB ~0dB)
Output	OUTPUT: RJ-45 for connection to PS-2406/4806 LINK: RJ-45 for daisy-chain connection with two additional PM-06

Specifications subject to modification without notice



SEIKAKU TECHNICAL GROUP LIMITED

NO.1 LANE 17, SEC.2, HAN SHI WEST ROAD, TAICHUNG 40151 TAIWAN

Tel: +886-4-22313737 Fax: +886-4-22346757 www.seikaku.hk