



BEAMZ
MADE
EAZY

152.829 V1.1

HYADEN

QUICK START GUIDE

CONTROL MENU

MENU		DESCRIPTION
ADDR	001-512	DMX address setting
CHND	10 Channels 23 Channels	DMX channel setting
SLND		NAST SL1
LOST		Blac Auto Soun Hold
SENS		000-099
LED		ON OFF
DISP	Normal Flip	Normal Flip
NAUN	000-255 000-255 000-255 000-255 000-255 000-255 000-255 000-255	RED GREEN BIUE WHITE LASE PAN DIM STRO
TEST		TEST
VER		Vxxx
DEFA		Default
RSET		Reset

DMX CHANNELS

10 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimmer 0-100%
		000-030	Strobe open
		031-090	Variable strobe slow to fast
		091-105	Strobe open
2	STROBE	106-165	Pulse effect slow to fast
		166-180	Strobe open
		181-240	Random strobe slow to fast
		241-255	Strobe open
		3	PAN
4	LASER EFFECT	000-015	No function
		016-039	Laser effect 1
		040-063	Laser effect 2
		064-087	Laser effect 3
		088-111	Laser effect 4
		112-135	Laser effect 5
		136-159	Laser effect 6
		160-183	Laser effect 7
		184-207	Laser effect 8
		208-231	Laser effect 9
5	LASER EFFECT SPEED	232-255	Laser effect 10
		000-255	Laser effect speed 0-100%
		000-015	No effect/No function
		016-020	Led effect1
		021-025	Led effect2
		026-030	Led effect 3
		031-035	Led effect4
		036-040	Led effect 5
		041-045	Led effect6
		046-050	Led effect 7
		051-055	Led effect 8
		056-060	Led effect9
		061-065	Led effect 10
		066-070	Led effect 11
		071-075	Led effect 12
		6	LED EFFECT
081-085	Led effect 14		
086-090	Led effect 15		
091-095	Led effect 16		
096-100	Led effect 17		
101-105	Led effect 18		
106-110	Led effect 19		
111-115	Led effect 20		
116-120	Led effect 21		
121-125	Led effect 22		
126-130	Led effect 23		
131-135	Led effect 24		
136-140	Led effect 25		
141-145	Led effect 26		

		146-150	Led effect 27
		151-155	Led effect 28
		156-160	Led effect 29
		161-165	Led effect 30
		166-170	Led effect 31
		171-180	Led effect 32
		181-185	Led effect 33
		186-190	Led effect 34
		191-195	Led effect 35
		196-200	Led effect 36
		201-205	Led effect 37
		506-210	Led effect 38
		211-215	Led effect 39
		216-222	Led effect colour mix
		223-229	Led effect colour mix
		230-236	Led effect colour mix
		237-243	Led effect colour mix
		244-250	Led effect colour mix
		251-255	Led effect colour mix
7	LED EFFECT SPEED	000-255	Led effect speed 0-100%
8	LASER 1-8	000-239	Laser 1-8 OFF
		240-255	Laser 1-8 ON
9	LED 1-7 MACRO	000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
		106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
10	RESET	000-250	No function
		251-255	Reset ALL

23 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	DIMMER	000-255	Master dimmer 0-100%
		000-030	Strobe on
		031-090	Variable strobe slow to fast
2	STROBE	091-105	Strobe on
		106-165	Pulse effect slow to fast
		166-180	Strobe on
		181-240	Random strobe slow to fast
		241-255	Strobe on
		3	PAN
4	LASER EFFECT	000-015	No function
		016-039	Laser effect 1
		040-063	Laser effect 2
		064-087	Laser effect 3
		088-111	Laser effect 4
		112-135	Laser effect 5
		136-159	Laser effect 6
		160-183	Laser effect 7
		184-207	Laser effect 8
		208-231	Laser effect 9
5	LASER EFFECT SPEED	232-255	Laser effect 10
		000-255	Laser effect speed 0-100%
		000-015	No effect/No function
		016-020	Led effect 1
		021-025	Led effect2
		026-030	Led effect 3
		031-035	Led effect 4
		036-040	Led effect5
		041-045	Led effect 6
		046-050	Led effect 7
		051-055	Led effect 8
		056-060	Led effect 9
		061-065	Led effect 10
		066-070	Led effect 11
		071-075	Led effect 12
		076-080	Led effect 13
		081-085	Led effect 14
		086-090	Led effect 15
		091-095	Led effect 16
		096-100	Led effect 17
		101-105	Led effect 18
		106-110	Led effect 19
		111-115	Led effect 20
		116-120	Led effect 21
		121-125	Led effect 22
		126-130	Led effect 23
		131-135	Led effect 24
		136-140	Led effect 25
141-145	Led effect 26		
146-150	Led effect 27		
151-155	Led effect 28		
6	LED EFFECT	151-155	Led effect 28

		156-160	Led effect 29
		161-165	Led effect 30
		166-170	Led effect 31
		171-180	Led effect 32
		181-185	Led effect 33
		186-190	Led effect 34
		191-195	Led effect 35
		196-200	Led effect 36
		201-205	Led effect 37
		506-210	Led effect 38
		211-215	Led effect 39
		216-222	Led effect colour mix
		223-229	Led effect colour mix
		230-236	Led effect colour mix
		237-243	Led effect colour mix
		244-250	Led effect colour mix
		251-255	Led effect colour mix
7	LED EFFECT SPEED	000-255	Led effect speed 0-100%
8	LASER 1	000-239	Laser 1 OFF
		240-255	Laser 1 ON
9	LASER 2	000-239	Laser 2 OFF
		240-255	Laser 2 ON
10	LASER 3	000-239	Laser 3 OFF
		240-255	Laser 3 ON
11	LASER 4	000-239	Laser 4 OFF
		240-255	Laser 4 ON
12	LASER 5	000-239	Laser 5 OFF
		240-255	Laser 5 ON
13	LASER 6	000-239	Laser 6 OFF
		240-255	Laser 6 ON
14	LASER 7	000-239	Laser 7 OFF
		240-255	Laser 7 ON
15	LASER 8	000-239	Laser 8 OFF
		240-255	Laser 8 ON
		000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
16	LED 1	106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
		000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
17	LED 2	106-135	White
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
18	LED 3	000-015	No function

		016-045	Red
		046-075	Green
		076-105	Blue
		106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
		000-015	No function
19	LED 4	016-045	Red
		046-075	Green
		076-105	Blue
		106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
		000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
20	LED 5	106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
		000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
21	LED 6	106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
		000-015	No function
		016-045	Red
		046-075	Green
		076-105	Blue
22	LED 7	106-135	White
		136-165	RGBW
		166-195	Red/Green
		196-225	Red/Blue
		226-255	Green/Blue
23	RESET	000-250	No function
		251-255	Reset all



BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



is a leading developer of lighting products, including intelligent DMX moving heads, wireless battery operated DMX effects, static washes, sound-activated club effects, strobes & blacklights, LED lighting, fog and special effects machines, lasers and indoor and outdoor architectural lighting, as well as lighting controllers and protective bags.

