PD-63A MKZ / GER-NL

DESCRIPTION

This 3-phase power distributor is designed to improve safety in both mobile, rental and fixed installations.

FEATURES

- This 3-phase power distributor is designed to improve safety in both mobile, rental and fixed installations.
- Connections output:
 - 2x CEE (3P+N+E) 32A outlet sockets (3x 32A, 5wire)
 - C 32 (32A 3P+N) 4-POLE automatic circuit breaker per 32A output
 - 3x earthed 16A mains outlet sockets (1 socket per phase)
 - C16 (16A 1P+N) 2-POLE automatic circuit breakers per 16A socket
- Connections input:
 - 1,5m long mains input cable (3x 63A, 5wire), equipped with CEE (3P+N+E) 63A inlet plug
 - Equipped with a 3P+N, 30mA residual current circuit breaker protects users against electrical shocks.
- Accurate digital 3-digit voltmeters per phase
- Accurate digital 3-digit ampere meters per phase
- Designed and build to the highest European and international safety standards.
- Oversized internal wiring for increased reliability!
- Extremely robust 19"/3U metal housing
- German 16A blue schukos (CEE 7/4)







www.briteq-lighting.com | https://www.facebook.com/Briteq

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2017 by BEGLEC NV. All rights reserved.

SPECIFICATIONS

DJ & Club, Stage & Rental, Theatre 11.74 No 160 black No 19" rack mountable 3U indoor No No No BRITEQ 5420025646406
Νο

YOUR DEALER



www.briteq-lighting.com | https://www.facebook.com/Briteq

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2017 by BEGLEC NV. All rights reserved.